

PLR BP1

Proloop Body Pack Induction Loop Receiver



Simple and convenient to use, this induction loop receiver is designed for use in induction-looped areas by listeners who do not wear T-coil-equipped hearing aids. Compatible with all IEC 60118-4 compliant induction loop systems.

FEATURES

- Operates up to 200 hours with two AA alkaline batteries
- Simple to use -- on/off volume control
- Internal tone control
- 3.5mm stereo jack
- Compatible with Williams Sound 2-bay and 12-bay chargers (CHG 3502 and CHG 3512). Chargers sold separately.
- 5-year warranty

Proloop Body Pack Induction Loop Receiver

Dimensions:	4.1"H x 2.85"W x 1.38"D (104 mm H x 72 mm W x 35 mm D).
Weight:	4.6 oz (130 g) with batteries, 2.6 oz (73 g) without batteries.
Color/Material:	Black ABS/polycarbonate molded plastic case.
Battery Type:	(2) AA (1.5VDC) Alkaline or NiMH (rechargeable).
Battery Life:	Up to 200 hours with Alkaline batteries.
LED Indicator:	Green LED indicates power on, flashes when batteries are low.
Headphone Jack:	3.5mm stereo TRS jack works with mono or stereo headphones.
Volume control:	External switched thumb wheel controls power on/off and volume level.
Tone control:	Rotary control inside battery compartment (1kHz reference at 400mA/m input with Tone at mid position)
Induction Coil:	Maximum reception: receiver oriented vertically
Power Output:	35mW (max) into 33 ohms mono impedance
THD:	<2%
Frequency Response:	300Hz to 10KHz, -6dB

NOTE: Specification subject to change without notice.

Architectural and Engineering Specifications

The receiver shall be a body pack style Induction loop receiver. It shall operate for up to 200 hrs with two AA Alkaline batteries and be housed in a black plastic enclosure. It shall have battery recharge ability utilizing Williams Sound drop-in chargers.

The receiver shall have a 3.5 mm headphone jack, on/off volume control. There shall be a tone control inside the battery compartment. It shall have a green power LED which will blink when the battery is low.

The receiver shall be covered under a 5 years parts and labor warranty.

This receiver shall be the Williams Sound model PLR BP1.

Domestic Sales

Williams Sound
10300 Valley View Rd
Eden Prairie, MN 55344
Ph: 800-328-6190 / 952-943-2252
FAX: 952-943-2174
Email: info@williamssound.com
Web: www.williamssound.com

International Sales

International Sales Department
Williams Sound
10300 Valley View Rd
Eden Prairie, MN 55344 USA
Phone: +1 952 943 2252
Fax: +1 952 943 2174
Email: info@williamssound.com
Web: www.williamssound.com



800.843.3544 / info@williamssound.com / www.williamssound.com